



AP5500 -G

PRACTICAC GENERATOR

- Simple design
- Full function & same quality
- Lower cost
- Stable output
- Low oil auto shutdown
- Longer running time
- OPTIONAL: Carbon monoxide detection



SPECIFICATION

Model	AP5500-G PRACTICAC GENERATOR
Frequency HZ	50/60
Rated output KW	5.0/5.5
Max.output KW	5.5/6.0
Rated voltage V	230/120/240
Phase number	Single phase
Voltage regulating type	AVR
Starting system	Manual/Electric
Fuel tank capacity L	25
Fuel consumption ratio L/H	2.65
Continuous running time h	9
Noise dB(A)25%@7m	74/76
Net weight KG	92
Package dimension mm	805*545*585
Engine	DK390
Displacement ml	389
Oil capacity L	1.1
Loading/20GP/40GP/40HQ	112/228/228
Certification	EPA/CARB/CE/EU5