



AP6500 -G

PRACTICAC GENERATOR

- Simple design
- Full function & same quality
- Lower cost
- Stable output
- Low oil auto shutdown
- Longer running time
- OPTIONAL: Carbon monoxide detection



SPECIFICATION

Model		AP6500-G PRACTICAC GENERATOR
Frequency HZ		50/60
Rated output KW		6.0/6.5
Max.output KW		6.5/7.0
Rated voltage V		230/120/240
Phase number		Single phase
Voltage regulating type		AVR
Starting system		Manual/Electric
Fuel tank capacity L		25
Fuel consumption ratio L/H		3.2
Continuous running time h		8
Noise dB(A)25%@7m		76/77
Net weight KG		95
Package dimension mm		805*545*585
Engine		DK420
Displacement ml		420
Oil capacity L		1.1
Loading/20GP/40GP/40HQ		112/228/228
Certification		EPA/CARB/CE/EU5